



LIGHTING KEY	
	B.05041 Track mounted emergency fitting 2 x 1W LED
	ML00.04 Front Light Track mounted adjustable spotlight 3000lm LED - Warm White Flood Optic
	BC23.7298 iRoll 85 up /down light 9.8W LED - Warm White Special finish - RAL 9004
	Tom Dixon Void pendant
	MPS Surface mounted emergency 3 x 1 W LED
	STANDARD TRACK Suspended standard 3 circuit mains voltage track. 1000mm and 2000mm lengths. 6771.04 - 1M track 6772.04 - 2M track MWVS1.04 - Power end MWR9.04 - End cap MWS2.04 - Connector MWS4.04 - Corner Section MWT1.04 - Flexible Connector MX66 - Suspension Cable
	LED strip 5m spool, 24W warm white 3000°K
NOTES:	EM exit signs TBC

NOTES:

GENERAL NOTES:

Area to be surveyed and all dimensions checked prior to any installation.

Listed Building. Great care must be taken while checking existing fixing points and establishing new ones during strip-out.

Contractor to visit site to establish and mark out fixing positions prior to fit out.

Once stripped out, contractor to liaise with design consultant, planning consultant and client for a visit with **Listed Buildings**, who will inspect and agree on fixings prior to any installation.

All fixings in accordance with detail drawings and 273/203.0 Method Statement

Area will have new finishes in situ such as floor, decorations, lighting and power. All to be protected during fit out period

Make good any decorations marked during fit out

GENERAL LIGHTING AND RCP NOTES:

Existing power fittings and locations not shown.

Contractor to survey existing power and pick up and reuse where possible.

Contractor to liaise with client on: security alarms, smoke alarms, CCTV and speaker system for specification, details and requirements, along with all other items not listed below.

No chasing in walls and ceilings, conduits to be concealed in or behind cabinetry where possible.

All new lighting to be supplied and installed in accordance with the specification provided by Iguzzini. Contractor to liaise with supplier on power requirements and fixings. www.iguzzini.com To be focussed after install by others

Contractor to ensure minimal fixings into existing structure. Iguzzini to advise on fixing details and power requirements. www.iguzzini.com

Refer to **273/003.0 Small power and flooring** to establish extent of works including final positioning of sockets, panic alarms, LCD screens etc.

ITEMS:

1/ Indicates track lighting with adjustable spot fittings. Lighting supplier to advise on spacing and number of fittings required, along with fixing details into existing structure.

2/ Indicates Tom Dixon Void pendants above cash desk, in copper, diameter 300mm

3/ Indicates wall mounted fittings in archway. Pointing upwards to soffit. Lighting supplier to advise on spec, along with fixing details into existing structure.

4/ Freestanding display cabinet with power for concealed LED strip lighting recessed into side faces. Iguzzini to specify LED strip light fittings. Socket and switch at low level. Contractor to liaise with supplier on installation and power requirements. www.iguzzini.com See **273/407.0** for cabinet detail and **273/003.0** for Power layout.

5/ New FE hanging sign, with power in galvanised conduit cables. Iguzzini to specify, along with fixing details into existing structure. Contractor to investigate behind FE sign and liaise with supplier for installation requirements and detail. www.iguzzini.com

6/ Contractor to ensure all fixtures are clear of existing ceiling pipes and AC boxing out, shown dotted. Heights as shown.

7/ Freestanding display window unit with power for concealed LED lighting recessed into side faces and top. Iguzzini to specify LED fittings. Socket and switch at low level. Contractor to liaise with supplier on installation and power requirements. www.iguzzini.com See **273/217.0** for cabinet detail and **273/003.0** for Power layout.

DECORATIONS

All existing pipes, beams, ceilings and ductwork **already painted**, to be rubbed down and prepared for decoration to match existing grey paint colour, TBC. Minimum 2 x coats matt emulsion and eggshell finish. Contractor to visit site and establish paint colour and finish, and to provide samples of all finishes stated for approval prior to manufacture.

Read in line with:
Iguzzini specification and install info
273/001.0 Demolitions and strip out
273/002.0 GA and setting out
273/003.0 Small power and flooring
273/101.0 and 273/102.0 Internal Elevations

DRINKALLDEAN

Ground Floor 32 St Oswalds Place London SE11 5JE
PHONE: +44 (0) 207 735 2731
info@drinkalldean.co.uk www.drinkalldean.co.uk

GENERAL NOTES: DO NOT SCALE FROM THIS DRAWING. REFER TO WRITTEN DIMENSIONS ONLY. ALL DIMENSIONS AND LEVELS TO BE CHECKED ON SITE BY THE CONTRACTOR. PRIOR TO COMMENCEMENT OF WORKS. ANY DISCREPANCIES TO BE REPORTED TO THE DESIGNER IMMEDIATELY AND PRIOR TO COMMENCEMENT OF WORKS. ALL DRAWINGS TO BE READ IN CONJUNCTION WITH WRITTEN SPECIFICATIONS / ASSOCIATED DOCUMENTATION SUPPLIED BY THE DESIGNER.	ALL DRAWINGS TO BE READ IN CONJUNCTION WITH CONSULTANT'S DOCUMENTATION AND DRAWINGS. ANY DISCREPANCIES BETWEEN CONSULTANT'S DRAWINGS TO BE REPORTED TO THE DESIGNER PRIOR TO COMMENCEMENT OF WORKS. THIS DRAWING SHOWS THE DESIGN INTENT ONLY THE CONTRACTOR SHALL ADVISE ON ALL DETAILS AND ENSURE STRENGTH AND STABILITY IN ALL CONSTRUCTION. THE CONTRACTOR TO PROVIDE SETTING OUT AND ROD DRAWINGS FOR APPROVAL PRIOR TO CONSTRUCTION. ALL SERVICES TO COMPLY WITH LOCAL AUTHORITY BUILDING CONTROL AND ENVIRONMENTAL HEALTH REQUIREMENTS AND TO SERVICES ENGINEERS DETAILS.	ALL STRUCTURE TO LOCAL AUTHORITY AND BUILDING CONTROL REQUIREMENTS AND TO STRUCTURAL ENGINEERS DETAILS AND CALCULATIONS. DO NOT SCALE THIS DRAWING. CHECK ALL DIMENSIONS ON SITE. THE CONTRACTOR SHALL COMPLY WITH: CON REGULATIONS DOTTING PRECAUTIONS. CODE OF PRACTICE FOR THE PREVENTION OF FIRES ON CONSTRUCTION SITES AND BUILDINGS UNDERGOING REFURBISHMENT ALL CONSTRUCTION AND MATERIALS TO CONFORM TO CURRENT BUILDING AND FIRE REGULATIONS.	SITE WASTE MANAGEMENT THE CONTRACTOR SHALL MANAGE ALL WASTE MATERIALS AND RE-USE / RECYCLE AS MUCH AS POSSIBLE TO MINIMISE WASTE. RISK ASSESSMENT THE CONTRACTOR MUST ENSURE THAT THE SITE IS A HAZARD FREE ENVIRONMENT AT ALL TIMES. STANDARD SAFETY CLOTHING AND EQUIPMENT MUST BE WORN AT ALL TIMES. THE CONTRACTOR MUST EMPHASISE POTENTIAL SITE RISKS AND HAZARD TO ALL OPERATIVES ESPECIALLY DURING DEMOLITIONS AND STRUCTURAL WORKS. IF IN DOUBT - ASK THE DESIGNER	DRAWING STATUS: FOR TENDER	CLIENT: CHURCHILL WAR ROOMS	DRAWING TITLE RCP and lighting
				REVISIONS:	PROJECT: CWR Shop	SCALE 1:50 @ A2 PAPER SIZE A2
					PROJECT ADDRESS: King Charles Street London SW1A 2AQ	DRAWN BY CJ DATE Sept 2015
						PROJECT NUMBER 273 DRAWING NUMBER 273/004.0 REVISION