

| FROM | LOCATION | TO | TERMINATING IN | LOCATION | CABLE TYPE |
|-------------------------------|------------------------------------|----|-------------------------------|-----------------------------|--|
| DMX Lighting Desk Input | Rear of Auditorium - High Level | | Input A DMX Merge Unit | AR Side of Stage | CAT5 Shielded Twin Twisted |
| Lighting Bar LX1 | Auditorium FOH | | Output 2 DMX Merge Unit | AR Side of Stage | CAT5 Shielded Twin Twisted |
| Lighting Bar LX2 | Over-stage | | Output 5 DMX Merge Unit | AR Side of Stage | CAT5 Shielded Twin Twisted |
| Lighting Bar LX3 | Over-stage | | Output 6 DMX Merge Unit | AR Side of Stage | CAT5 Shielded Twin Twisted |
| Lighting Bar LX4 | Auditorium Stage Left | | Output 1 DMX Merge Unit | AR Side of Stage | CAT5 Shielded Twin Twisted |
| Lighting Bar LX5 | Auditorium Stage Right | | Output 3 DMX Merge Unit | AR Side of Stage | CAT5 Shielded Twin Twisted |
| DMX Facility Panel | Stage Right Floor Level | | Output 4 DMX Merge Unit | AR Side of Stage | CAT5 Shielded Twin Twisted |
| DMX Lighting Control Position | Rear of Auditorium - High Level | | Sound System Location | Right Side Hall | CAT5 Shielded Twin Twisted |
| Projector Position | Centre of Auditorium - High Level | | Sound System Location | Right Side Hall | CAT5 Shielded Twin Twisted |
| Projector Position | Centre of Auditorium - High Level | | Sound System Location | Right Side Hall | HDMI Ext |
| Projection Screen Control | Over the Proscenium Arch | | Sound System Location | Right Side Hall | 4 core 1.5mm 3184Y Flex |
| Projector Screen | Over the Proscenium Arch | | Distribution Board Non-Dim 11 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Stage Mic Facility Panel | Microphone Stage Right Floor Level | | Sound Mixer input 1 | A Right Side of Hall | Van Damme Pro Grade Classic XKE 1 pair Install Cable |
| Stage Mic Facility Panel | Microphone Stage Right Floor Level | | Sound Mixer input 2 | A Right Side of Hall | Van Damme Pro Grade Classic XKE 1 pair Install Cable |
| Stage Mic Facility Panel | Microphone Stage Left Floor Level | | Sound Mixer input 3 | A Right Side of Hall | Van Damme Pro Grade Classic XKE 1 pair Install Cable |
| Stage Mic Facility Panel | Microphone Stage Left Floor Level | | Sound Mixer input 4 | A Right Side of Hall | Van Damme Pro Grade Classic XKE 1 pair Install Cable |
| Lighting Bar LX1 | Auditorium FOH | | Distribution Board Non-Dim 2 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX1 | Auditorium FOH | | Distribution Board Non-Dim 3 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX2 | Over-stage | | Distribution Board Non-Dim 5 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX2 | Over-stage | | Distribution Board Non-Dim 6 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX3 | Over-stage | | Distribution Board Non-Dim 7 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX3 | Over-stage | | Distribution Board Non-Dim 8 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX4 | Auditorium Stage Left | | Distribution Board Non-Dim 1 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX5 | Auditorium Stage Right | | Distribution Board Non-Dim 4 | AR Side of Stage | 6242Y 2.5 Twin & E |
| Lighting Bar LX1 | Auditorium FOH | | D2 - Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX1 | Auditorium FOH | | D3- Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX2 | Over-stage | | D5 - Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX2 | Over-stage | | D6 - Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX2 | Over-stage | | D7- Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX3 | Over-stage | | D8- Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX3 | Over-stage | | D9- Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX3 | Over-stage | | D10- Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX4 | Auditorium Stage Left | | D1 - Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Lighting Bar LX5 | Auditorium Stage Right | | D4 - Cord Patch Unit | High Level Rear Stage | ? Use existing cables |
| Sound System Location | Auditorium Stage Right | | Active Speaker A Right | Hall Side Wall 2500 off FFL | Van Damme Pro Grade Classic XKE 1 pair Install Cable |
| Sound System Location | Auditorium Stage Right | | Active Speaker A Left | Hall Side Wall 2500 off FFL | Van Damme Pro Grade Classic XKE 1 pair Install Cable |
| Active PA Speaker | Auditorium Wall Stage Right | | Distribution Board Non-Dim 12 | A Right Side of Hall | 2.5 sq mm 6242Y Cable |
| Active PA Speaker | Auditorium Wall Stage Left | | Distribution Board Non-Dim 12 | A Right Side of Hall | 2.5 sq mm 6242Y Cable |

Probus Village Hall
Amelia Close, Probus. TR2 4NB

Job Title: STAGE REFURBISHMENT
Drawing Title: WIRING SCHEDULE

Date: 10/08/2021
Scale: NTS
Sketch No: PVH005
Rev: Tender Issue